




Features:

- ✓ Support 5.1 Dolby / DTS / Dolby Prologic II.
- ✓ Prologic II Modes: MOVIE , MUSIC , MATRIX , VIRTUAL , EMULATION
- ✓ 24bit High-Performance DAC and ADC.
- ✓ Inbuilt Bass Management
- ✓ 80Hz Crossover High pass and Low pass
- ✓ Full featured LED status

5.1 DTS / DOLBY DECODER

FT003 VER 2

1 LED STATUS :

-  If received and decoding DD (AC3) audio will glow DOLBY LED.
-  If received and decoding DTS audio will glow DTS LED.
-  if PCM audio received and PRO II decoded will glow PCM LED.

STATUS LED

| | |
|----------------|---|
| OFF | : Signal not connected. |
| SOLID BLUE | : Source connected but no audio signal. |
| 15Sec BLINKING | : Source connected and audio is decoding. |
| 500mS BLINKING | : ARC Connecting ... |
| FAST BLINKING | : Board Fault |

2 GPIO :

LED Panel Communication Output (Optional)

3 AUDIO OUTPUTS :

5.1 channel decoded analog output
Output Volt - 2 Vrms

4 AUDIO INPUT :

AUX (STEREO ANALOG INPUT)

5 SOURCE SELECTION AB CONTROL :

A = LOW , B = HIGH : OPTICAL,
A = HIGH , B = LOW : COAXIAL,
A = LOW , B = LOW : TV(ARC) ,
A = HIGH , B = HIGH : AUX,

PWR = HIGH : Decoder Power off ,

PWR = LOW : Decoder Power on ,

6 POWER :

+8 to 24 Volt DC single power supply.

AB CONTROL

